



Squirrel-Free Electronic Bird Feeder


INSTRUCTIONS

IMPORTANT: Keep these instructions for future maintenance and to keep your Feeder in excellent working condition.

PLEASE READ CAREFULLY!!!!

Included: Hood, Hopper, Seed Tray, Hook, Wing Nut, Upper Portals & Perches. All other parts are factory assembled and ready to use.

**Always use a 9V alkaline battery (not included).
Change the battery every 3 months, sooner if needed.**



Follow Instructions Carefully to ensure proper use and operation of feeder.

1. Insert the green perches through the holes of the feeder portals (see fig.2). Snap the V-shape end of the perches securely into the back recessed area of each portal.

NOTE: The perches can be arranged in any way that you prefer. You may also choose to not use all the perches to allow clinging birds easier access to some feeder ports. And remember, different size birds prefer different length perches.

2. Attach the feeder portals to the seed hopper (seed holding bin) with the curved side in and the perch out (see fig.3). First, hook the two lower notches of the feeder port onto the lip of the porthole. Then, firmly push the top notch of the feeder port into the seed hopper's porthole until it snaps. Feeder portals will lock into the seed hopper securely.

NOTE: Be sure to have a tight grip on the hopper when inserting the feeder portals. Inserting them requires pressure—this will not break the feeder.

3. With the ON/OFF switch on the off position, insert the 9V battery into the base. Make sure battery firmly snaps into the battery connector clips. Attach the feeder tray to the base of the seed hopper, securing the tray with the wing nut (see fig.4).

NOTE: The feeder tray is not flat. Install the tray so that the raised portion in the center of the tray fits up into the base of the seed hopper. Secure with wing nut.

4. Make sure the black rubber grommet is in the center hole of the hood/baffle lid. If it is not in place, firmly push the black rubber grommet back into the baffle (see fig.5).

5. Put a drop or two of liquid dish detergent into the hole of the grommet. This will help the hanger rod to slide through more easily.



6. Slide the small hook end of the hanger rod through the grommet in the top of the hood/baffle lid. Push down with your thumb and, at the same time lift up with your fingers to slide the hanger rod through the grommet (see fig.6).

NOTE: To keep the grommet in place, apply pressure to the bottom of the grommet while sliding the hanger rod through. Rubber grommet prevents the metal rod from contacting the metal surface on the top.




7. Connect the center wire by plugging in the male connection at the end of the white wire into the female connection in the hood/baffle lid. This will make the electronic connection to the top of the feeder (see fig.7).




8. Hook the hanger rod through the loop in the center rod inside the seed hopper (see fig.8).

9. Holding the feeder by the hanger rod, gently push the hood/baffle top down to the top of the seed hopper.

10. Hang feeder following instructions on the back of this sheet and turn the ON/OFF switch to the ON position.



Optional Tester available for purchase to test your birdfeeder. **The feeder cannot be tested using a screwdriver, voltmeter or ohmmeter**—these meters can damage the feeder's circuitry making the feeder and the meter inoperable.



Optional Pole Mount Adapter Kit available for purchase to allow the Squirrel Free Birdfeeder to be mounted on a pole. Includes hardware, does not include pole.

Nature Needs, Inc. • P.O. Box 2051 • Aston, PA 19014
Tel: 610-459-1775 • Fax: 610-358-4979 • Email: sales@natureneedsinc.com

WildBills is a registered trademark of Nature's Needs Inc., USA WildBills products are covered by various patents, both domestic and foreign. All you'll feed are birds. Trademark owner: Nature's Needs Inc. The WildBills squirrel-free Bird Feeder is a patent-protected product of Nature's Needs Inc., Aston, Pennsylvania, 19014. U.S. Patent No. 5,150,655, 5,191,857 and Canada Patent No. 2,091,368. Made in USA.

NOTE: ALWAYS TURN YOUR BIRDFEEDER OFF WHILE DOING ANY TYPE OF MAINTENANCE SUCH AS CLEANING, FILLING OR REPLACING THE BATTERY.